

# 805PT Pressure Transmitter

Form 1360CM

# The 805PT pressure

transmitter is a compact loop-powered transmitter. A 1-5VDC low power option is also available. It's rugged construction makes cost of ownership low and it carries a three-year warranty. The 805PT Pressure Transmitter is suitable for hazardous locations and hostile environments where space is limited. It meets applications where low-cost, continuous monitoring is preferred. Zero and span are field adjusted via calibration kit with USB communication cable.

### **Features**

- Compact, 316 Stainless Steel, hermetically sealed enclosure
- 17-4 Stainless Steel sensor, no O-ring
- 0.25% accuracy
- 4-20 mA or 1-5 VDC output
- EMI/RFI protection
- NEMA 4X, IP 66 housing
- FM and ATEX certified for hazardous locations in U.S., Canada and Europe
- Dual Seal approval









## **Product Specifications**

Accuracy (Linearity, H	Accuracy ±0.25% URL (BFSL) (Linearity, Hysteresis and Repeatability)		
Turndown	5:1 2:1 for 100 psi range		
Zero Offset	+10% URL		
Temperature Range Compensated	-40 to 176°F (-40 to 80°C)		
Ambient Process	-40 to 176°F (-40 to 80°C) -40 to 194°F (-40 to 90°C) -40 to 194°F (-40 to 90°C)		
Storage Temperature Effect	±1% URL/100°F @ -40 to 176°F		
Long Term Stability	≤±0.5% URL per year		
Response Time	≤ 5 ms		
Supply Voltage	8-30VDC		
Output 4 to 20 mA (1-5 VDC option - 27mW ± 5mW @ 9VDC)			
Loop Resistance	800 ohms @ 24VDC		

Circuit Protection	Reverse polarity and EMI/RFI protected
Construction	316SS housing (CF8M)
Process Connection	1/2" NPT(M) with 1/4" NPT(F) 17-4SST
Size	1/2" NPT(M)
Termination	18 AWG shielded cable, 72-inch length
Wetted Materials	17-4SST
Over Pressure	
0-100 psi	3 times FSPR
Up to 10000 psi	2 times FSPR
Burst Pressure	
0-100 thru 0-250	psi 40 times FSPR
0-500 thru 0-1000	0 psi 20 times FSPR
0-2500 psi	10 times FSPR
0-5000 psi	8 times FSPR
0-10000 psi	4 times FSPR
Weight	1.8 lb (0.8 kg)
Warranty	3 years

Design and specifications are subject to change without notice. For latest revision, see c-a-m.com/measurement.

**Model Number System** 

**How to Order** 

### 805PT - C07 - A - RR9A

805PT pressure transmitter with 4-20mA output, 0-2500 psi, 17-4SS port, 1/2" NPT(M) with 1/4" NPT(F) and optional SS tag wired to housing with customer specified information.

3 Process Connection Size

1/2"NPT(M) with 1/4"NPT(F)

4	Accessories	
ВВ	Cleaned for industrial oxygen service	
DS	Dual Seal approval (FM)*	
НВ	SS universal terminal box, 1/2" NPT(F), ATEX approved	
нвме	SS universal terminal box, M20 x 1.5(F), ATEX approved	
НТ	SS universal terminal box, 1/2" NPT(F), CSA certified	
PK	Pipe mounting kit	
RR	SS tag wired to housing with customer specified information	
RR	9A     Model Number	

#### **Test Certificates**

805 PT	Certificates*	C1	C2	C3	C4	C8
	Calibration	•				
	Hydrostatic Pressure Test		•			
	Inspection Report			•		
	Compliance / Conformance				•	
	Typical Material of Wetted Parts					•

Α

• Calibration Kit for adjusting range (includes hardware and software): Part Number 9231026.

<sup>\*</sup> Dual Seal version is not hermetically sealed

<sup>\*</sup>Add certificate code to the end of model number.

# **Pressure Transmitter**


### **Agency Approvals**

Approved*	Safety Method	Approval
FM (U.S. and Canada)	Explosion Proof Hazardous Locations	Class I, II, III; Division 1 Groups A-G; T5; Type 4X
	Non-incendive	Class I, II, III; Division 2 Groups A-G; T5; Type 4X
ATEX or INMETRO	Flameproof	II 2 G Ex d IIC T5 IP 66

### **Dimensions**

Dimensions shown are for reference only. Contact the factory for certified dimension drawings. Linear = mm/in.

Drawing 0091438





#### **NORTH AND SOUTH AMERICA**

14450 JFK Blvd. Houston, TX 77032 USA Tel 1 281 582 9500 ms-us@c-a-m.com

7300 Nix Dr.
Duncan, OK 73533
USA
Tel 1 580 470 9600
ms-us@c-a-m.com

1000 McClaren Woods Dr. Coraopolis, PA 15108 USA Tel 1 724 273 9300 gasufm@c-a-m.com

7944 10th Street NE Calgary, Alberta T2E 8W1 Canada Tel 1 403 291 4814 ms-canada@c-a-m.com

### **EUROPE, AFRICA, CASPIAN AND RUSSIA**

3 Steyning Way
Southern Cross Trading Estate
Bognor Regis
West Sussex PO22 9TT
England, UK
Tel 44 1243 826741
ms-uk@c-a-m.com

### **ASIA PACIFIC AND MIDDLE EAST**

Suite 16.02 Menara AmFirst No. 1 Jalan 19/3 46300 Petaling Jaya Selangor Darul Ehsan Malaysia Tel 603 7954 0145 ms-kl@c-a-m.com

Level 9, Al Jazira Club Tower A P.O. Box 47280, Muroor Road Abu Dhabi United Arab Emirates Tel 971 2 596 8400 ms-uk@c-a-m.com

Learn more about Cameron's measurement solutions at: www.c-a-m.com/measurement

